



September 2002

DATA SHEET

12V lamp for Survival Craft External Light (Flashing) type **Rescue-Master 12V**.
Approved according to latest IMO Res. MSC. 81(70).

Power source (not included):	12V battery.
Light intensity:	Min. 4,3 candela.
Light duration:	Min. 12 hours.
Operational temperature:	-30 C to +65 C
Storage temperature:	-30C to +65 C
Weight:	Approx. 120 grams.

RESCUE-MASTER 12V
SURVIVAL CRAFT EXTERNAL LIGHT
LAMP ONLY

Test & Service Instructions

- This lamp is intended for motorized survival crafts to be connected to the crafts 12V electrical system.
- The lamp is polarized, so when connected correctly, the lamp is flashing. *Incorrect connection will result in a steady light.*
- The bulb can be replaced by unscrewing the cap's 4 screws. Replace the bulb only with original bulb from Daniamant.
- Replace the bulb after 12 hours use.
- Replace complete lamp if found faulty.

DANIAMANT ApS - INDUSTRIVEJ 24C - DK 3550 SLANGERUP - PHONE: +45 47 373800
CVR-NR.:50 96 76 11- TELEFAX: +45 47373809 - BANK: NORDEA: 2217 7558 164 136
Email: office@daniamant.com